

# P&E Motive Power Soft Roster

SW7	1201	1202	1203	1204																
SW1500	1501	1502	1503	1504	1505															
MP15DC	1601	1602	1603																	
MP15AC	1701	1702	1703																	
GP9	2001	2002	2003	2004	2005	2006	2007	2008	2009											
GP-30	3001	3002	3003	3004	3005	3006	3008	3009	3010	3011										
GP35	3101	3102	3103	3104	3105															
GP-38	2101	2102	2103	2104	2105	2106	2107	2108												
GP-38-2	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111									
GP39-2	3201	3202	3203	3204																
GP40-2	3501	3502	3503	3504	3505	3506	3507	3508	3509	3510	3511	3512	3513							
GP60	3701	3702	3703	3704	3705	3706	3707	3708	3709	3710										
SD9	4001	4002	4003	4004	4005	4006	4007	4008	4009	4010	4011	4012	4013	4014	4015					
SD35	4101	4102	4103	4104																
SD38	4150	4151	4152	4153	4154															
SD40-2	4201	4202	4203	4204	4205	4206	4207	4208	4209	4210										
SD45T-2	4500	4501	4502	4503																
SDP35	4105																			
U33B	5001	5002	5003																	
U330B	5104																			

red means that the number was taken

grey= hard roster

Yellow= Soft roster